



Coemar ParLite LED - DMX 512 Functions

channel	function	type of control effect		decimal		percentage		
1	master	proportional adjust luminous output intensity from 0 to 100%	0	-	255	0%	-	100%
	dimmer							
2	red	proportional proportional control of the percentage of red colour from 0 to 100%	0	-	255	0%	-	100%
2 (A)	speed	proportional fade speed between colours of the program selected from channel 6; from fast to slow (from 1 second to 1 minute)	0	-	255	0%	-	100%
Note 1: the second function 2 (A) is enabled when channel 6 is active								
3	green	proportional proportional control of the percentage of green colour from 0 to 100%	0	-	255	0%	-	100%
		control of the pause time between colours (steps) of the program						
3 (A)	pause	proportional selected from channel 6; the pause time is adjustable proportionally from 1 second to 3.30 minutes	0	-	255	0%	-	100%
Note 2: the second function 3 (A) is enabled when channel 6 is active								
4	blue	proportional proportional control of the percentage of blue colour from 0 to 100%	0	-	255	0%	-	100%
		step no effect	0	-	9	0%	-	4%
		proportional variable speed strobing effect, from slow to fast	10	-	57	4%	-	22%
		step stop strobe	58	-	59	23%	-	23%
		proportional sequenced pulse effect, slow closing, fast opening (variable speed pulsing, from slow to fast)	60	-	108	24%	-	42%
		step stop strobe	109	-	110	43%	-	43%
	strobe							
5	effect	proportional sequenced pulse effect, fast closing, slow opening (variable speed pulsing, from slow to fast)	111	-	159	44%	-	62%
		step stop strobe	160	-	161	63%	-	63%
		proportional random strobe effect with variable speed from slow to fast and synchronised colours	162	-	207	64%	-	81%
		step stop strobe	208	-	209	82%	-	82%
		proportional random strobe effect with variable speed from slow to fast and non-synchronised colours	210	-	255	82%	-	100%
		no effect	0	-	9	0%	-	4%
		automated program 1	10	-	50	4%	-	20%
		automated program 2	51	-	91	20%	-	36%
6	automated	step automated program 3	92	-	132	36%	-	52%
	functions							
		automated program 4	133	-	173	52%	-	68%
		random program repeat	174	-	214	68%	-	84%
		repeat all programs in sequence	215	-	255	84%	-	100%
Projector: Par Lite Led		Table name: DMX 512 functions, number 263, Edition 0 dated 7/10/2005						